

NTE1394
5.5W Dual Power Amplifier
Car Radio, Car Stereo Output
Audio Power Amplifier

Features:

- Dual Mode or Bridge Connection Mode Type.
- Some Protection Circuits Included
- Thermal Protection, Over Voltage Protection, Current Limiter, BTL DC Short Protection.
- Wide Operating Voltage Range: $V_{CC(opr)} = 8V$ to $18V$
- A chassis mounting is easily designed using SIP (Single in Line Package) 12 Pins
- This Power IC Obtains High Output Power by Bridge Connection: $P_{OUT} = 17W$ (Typ) at $V_{CC} = 13.2V$, $R_L = 4\Omega$, THD = 10%
- Dual Mode: Minimum Load Impedance is 2 ohm
 BTL Mode: Minimum Load Impedance is 4 ohm

Absolute Maximum Ratings: ($T_A = +25^\circ C$ unless otherwise specified)

Peak Supply Voltage, V_{CC} surge	45V
DC Supply Voltage (30 sec), V_{CCDC}	25V
Operating Supply Voltage, V_{CCopr}	18V
Output Current (Peak), $I_{O(peak)}$	4.5A
Power Dissipation, P_D	25W
Operating Temperature Range, T_{opr}	-30° to $+75^\circ C$
Storage Temperature Range, T_{stg}	-55° to $+150^\circ C$

Electrical Characteristics:

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Quiescent Current	I_{CCQ}		–	85	200	mA
Output Power Dual	P_{OUT}	THD = 10%	4.5	5.5	–	W
		THD = 10%, $R_L = 2\Omega$	–	8	–	W
		BTL THD = 10%	14	17	–	W
Maximum Output Power Dual	P_{OM}	$V_{IN} = 100mV_{rms}$	–	9	–	W
			BTL	–	30	–

Electrical Characteristics (Cont'd):

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Total Harmonic Distortion Dual	THD	$P_{OUT} = 1W$	-	0.2	1.5	%
BTL			-	0.3	1.5	%
Voltage Gain	G_V	$V_{OUT} = 0dBm$	52.5	54.0	55.5	dB
Channel Balance	ΔG_V	$V_{OUT} = 0dBm$	-	0	± 1.0	dB
Channel Separation	CT	$V_{OUT} = 0dBm$	-	0	± 1.0	dB
Ripple Rejection Dual	RR	$f = 100Hz$	-	-20	-	dB
BTL			-	-29	-	dB
Input Resistance	R_{IN}		20	35	50	k Ω
Output Noise Voltage	V_{NO}	$R_g = 10k\Omega, BW = 50Hz \text{ to } 20kHz$	-	1	2	mV _{rms}

Pin Connection Diagram
(Front View)

