


SOT223 NPN SILICON PLANAR MEDIUM POWER TRANSISTORS

**BSP41
BSP43**

ISSUE 3 – NOVEMBER 1995

COMPLEMENTARY TYPES – BSP43 - BSP33
BSP41 - BSP31

PARTMARKING DETAIL – DEVICE TYPE IN FULL



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	BSP41	BSP43	UNIT
Collector-Base Voltage	V_{CBO}	70	90	V
Collector-Emitter Voltage	V_{CEO}	60	80	V
Emitter-Base Voltage	V_{EBO}	5		V
Peak Pulse Current	I_{CM}	2		A
Continuous Collector Current	I_C	1		A
Base Current	I_B	100		mA
Power Dissipation at $T_{amb}=25^\circ\text{C}$	P_{TOT}	2		W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150		$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage BSP43 BSP41	$V_{(BR)CBO}$	90 70		V	$I_C=100\mu\text{A}$
Collector-Emitter Breakdown Voltage BSP43 BSP41	$V_{(BR)CEO}$	80 60		V	$I_C=10\text{mA}$ *
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	5		V	$I_E=10\mu\text{A}$
Collector Cut-Off Current	I_{CBO}		100 50	nA μA	$V_{CB}=60\text{V}$ $V_{CE}=60\text{V}$, $T_{amb} = 125^\circ\text{C}$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		0.25 0.5	V V	$I_C = 150\text{mA}$, $I_B = 15\text{mA}$ $I_C = 500\text{mA}$, $I_B = 50\text{mA}$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		1.0 1.2	V V	$I_C = 150\text{mA}$, $I_B = 15\text{mA}$ $I_C = 500\text{mA}$, $I_B = 50\text{mA}$
Static Forward Current Transfer Ratio	h_{FE}	30 100 50	300		$I_C = 100\mu\text{A}$, $V_{CE}=5\text{V}$ $I_C = 100\text{mA}$, $V_{CE}=5\text{V}$ $I_C = 500\text{mA}$, $V_{CE}=5\text{V}$
Collector Capacitance	C_c		12	pF	$V_{CB} = 10\text{V}$, $f = 1\text{MHz}$
Emitter Capacitance	C_e		90	pF	$V_{EB} = 0.5\text{V}$, $f = 1\text{MHz}$
Transition Frequency	f_T	100		MHz	$I_C=50\text{mA}$, $V_{CE}=10\text{V}$ $f = 35\text{MHz}$
Turn-On Time	T_{on}		250	ns	$V_{CC}=20\text{V}$, $I_C = 100\text{mA}$
Turn-Off Time	T_{off}		1000	ns	$I_{B1} = I_{B2} = 5\text{mA}$

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$
For typical characteristics graphs see FMIMT493 datasheet.